Uniblitz® NS35B

35mm Bi-Stable Optical Shutter

Overview

The Uniblitz NS35B is a 35mm-aperture bi-stable optical shutter utilizing our patented N-CAS® technology. The NS35B's simple design provides maximum clearance around the aperture, and a machined flat surface makes for its easy integration into virtually any system. The NS35B has an overall diameter of 3.18 inches, and an electronic synchronization is available. Bi-stable shutter devices, like the NS35B, require no power to hold the blades in either the open or closed state.

Key Features

- 35mm aperture
- Only two unique moving parts
- Can be configured for the <u>VED24</u>,
 ED12DSS, or VDM1000 drivers
- RoHS Compliant
- Transfer time on opening:
 12.0 milliseconds
- Transfer time on closing:12.0 milliseconds

Specifications

Electrical Specifications

Coil resistance 6 OHMS ¹

Voltage to Open +10.7 VDC ²

Hold Voltage (Nominal) N/A

Mechanical Specifications

Weight Unhoused 70.0 gOperating Temp. $0 - 80 \,^{\circ}\text{C}$

Max. Opening Bounce 15%

Max. Closing Bounce 5%

Max. Freq. of Operation ³ 2 Hz / 5 Hz

Number of Shutter Blades 5




¹ Two 12 ohm coils wired in parallel.

² Peak voltage as provided by the VED24 Driver.

³ (Continuous/Burst) Continuous frequency rating specified at shutter's minimum exposure pulse. Burst frequency rating specified for four (4) seconds maximum with one (1) minute minimum between bursts.

Shutter Timing Data



¹ Under no circumstances should any type of lubricant be applied to the shutter blade area. Lubricating the shutter blades will likely slow the shutter down and may eventually render it inoperable.

O - ADelay time on opening after current applied6.5A - CTransfer time on opening12.0O - CTotal opening time18.5C - EMin. dwell time with min. input pulse7.0B - FMin. equivalent exp. time4.0D - EDelay on closing after current applied19.0E - GTransfer time on closing12.0A - GTotal window time31.0	NS35B (w/ VDM1000 and "T" blades) ¹ Time (msec.)		
O-C Total opening time 18.5 C-E Min. dwell time with min. input pulse 7.0 B-F Min. equivalent exp. time 4.0 D-E Delay on closing after current applied 19.0 E-G Transfer time on closing 12.0	O - A	Delay time on opening after current applied	6.5
C - E Min. dwell time with min. input pulse 7.0 B - F Min. equivalent exp. time 4.0 D - E Delay on closing after current applied 19.0 E - G Transfer time on closing 12.0	A - C	Transfer time on opening	12.0
B-F Min. equivalent exp. time 4.0 D-E Delay on closing after current applied 19.0 E-G Transfer time on closing 12.0	O - C	Total opening time	18.5
D - E Delay on closing after current applied 19.0 E - G Transfer time on closing 12.0	C - E	Min. dwell time with min. input pulse	7.0
E-G Transfer time on closing 12.0	B - F	Min. equivalent exp. time	4.0
0	D - E	Delay on closing after current applied	19.0
A - G Total window time 31.0	E - G	Transfer time on closing	12.0
	A - G	Total window time	31.0
MET Min. exposure time 20.0	MET	Min. exposure time	20.0
TEP Typical exposure pulse >20.0	TEP	Typical exposure pulse	>20.0

Product Options

NS35B 2345-6-7

1 Shutter Series:

NS35B

2 Housing:
 3 Blades: ²
 4 Electronic Sync:
 1: Un-Housed
 T: Low Energy (Teflon®)
 Comitted
 Lincluded

Connector:

L: 18" Flying Leads

Leave blank for 5-pin
Switchcraft® connector
with 6" harness

6 Encapsulated Coil:

EC: Included

Leave blank if not required

Driver Compatibility:

ED: ED12DSS compatibility

VED: VED24 compatibility

Leave blank for VDM1000 compatibility


Ex: NS35B1T0L-EC-VED

² Other blade coating options may be available by special order.

³ Input side only; Teflon® coating is on opposite side to protect shutter blade surface. Light source must be input to the reflective side only.

Electronic Sync.

The synchronization system for NS shutter devices incorporates a small magnet mounted to the driving mechanism and a Hall effect sensor. When the device achieves approximately 80% of full open, the magnet causes the Hall effect sensor to change state, producing a signal to indicate that the shutter has switched to the active state. Shown to the left is the NS series shutter schematic which incorporates the electronic synchronization system. There is no connection to the designated synchronization pins when an electronic sync. is not selected.



Uniblitz® NS35B Technical Drawings

Shutter Layout

